

ENERGY ELEMENT

WER3000FSI14-16-A

| Order no. | WER3000FSI14-16-A |
|-----------------------------------|---|
| Series | WER3000 |
| Transmission mode | electrical |
| Function | Signal current and connection options for sensors of the tool changer |
| Compatible with installation size | WPR5100 / WPR5125 / WPR5160 / WPR5200 / WWR1160 / WWR1200 |
| Compatible with | Fixed part |
| No. of contacts | 14+5 Sensoric |
| Connection type | Spring contacts |
| Nominal current [A] | 3 |
| Supply voltage [V] | 60 |
| Fixing thread | M23 |
| Connection type | Male connector |
| Connection type | Round plug |
| Connection alignment | radial or axial |
| Sensor linkage | Left |
| Connection sensor X1 | Female connector M8, 3-pole |
| Connection sensor X2 | Female connector M8, 4-pole |
| Joining force [N] | 19 |
| Release force [N] | - |
| Certifications | LABS / REACH / RoHS |
| Protection to IEC 60529 | IP54* |
| Weight [kg] | 0.15 |

*only in coupled state



