

ENERGY ELEMENT

WER3000FSI14-17-A

► Technical Data

Order no.	WER3000FSI14-17-A
Series	WER3000
Transmission mode	electrical
Function	Signal current and connection options for sensors of the WWR
Compatible with installation size	WWR / WWR1000 - 100 / 125 / 160 / 200
Compatible with	Fixed part
No. of contacts	14+5 Sensoric
Connection type	Spring contacts
Nominal current [A]	3
Supply voltage [V]	60
Fixing thread	M23
Connection type	Male
Connection type	Round plug
Connection alignment	radial or axial
Sensor linkage	Right
Connection sensor X1	Socket M8, 3-pole
Connection sensor X2	Socket M8, 4-pole
Joining force [N]	19
Release force [N]	-
Protection to IEC 60529	IP54*
Weight [kg]	0.15

*only in coupled state



